

## PRODUCT DATASHEET

**Type:** eNEXHO-CR  
**Art. Nr.:** 38905



### Short description

Funkbus radio power actuator, 868MHz, 230V, 16A, on/off



### Product Description

The ETHERMA NEXHO CR radio bus module enables switching of electrical loads up to 3500 W. Any electrical load can be switched on and off via pushbutton. Once installed and integrated into the ENX system at the touch of a button, each individual module can be assigned to different scenarios and controlled, viewed and changed using a smartphone, tablet or PC. It can also be used as an actuator for other modules. Due to the compact design, all modules can be mounted in a deep switch box, in the suspended ceiling or in the distribution board, 12, 24, 230 V, 16 A, switching capacity: max. 3500 W, radio frequency: 868 MHz, 35x50x42 mm, CE marking.

### ETIM characteristics

<b>Bus system KNX</b>	×	<b>Width in number of modular spacings</b>	3
<b>Bus system KNX-RF (Radio Frequency)</b>	×	<b>Number of digital inputs</b>	0
<b>Bus system radio frequency</b>	✓	<b>Max. switching power</b>	3600 Watt
<b>Bus system LON</b>	×	<b>Max. switching power LED</b>	3600 Watt
<b>Bus system Powernet</b>	×	<b>Output power</b>	3600 Watt
<b>Other bus systems</b>	None	<b>Max. number of switching contacts</b>	1
<b>Radio frequency bidirectional</b>	✓	<b>Max. switching current</b>	16 Ampere
<b>Mounting method</b>	Built-in installation	<b>Rated current</b>	16 Ampere
<b>Local operation/hand operation</b>	×	<b>Rated operating voltage</b>	230 230 Volt
<b>With LED indication</b>	✓	<b>Min. depth of built-in installation box</b>	50 Millimetre
<b>Suitable for C-load</b>	×		
<b>Different phases connectable</b>	✓		
<b>With bus connection</b>	×		
<b>Bus module detachable</b>	×		
<b>Modular expandability</b>	×		
<b>Degree of protection (IP)</b>	IP20		

Created on: 27/11/2023