

## PRODUCT DATASHEET


**Type:** ET-111A  
**Art. Nr.:** 36758



9120015729282

### Short description

Radio receiver, 16A, surface mount



### Product Description

The ET-111A radio receiver, in conjunction with the ET-14A radio room thermostat, enables simple switching of heating or cooling devices. The 868 MHz frequency range guarantees a long range and optimum connection. The ET-111A switches 16 A and can be mounted on the wall or a flush-mounted box 100 / 100. Switching current: 16 A, dimensions: 140x54x25 mm, protection class: IP 20, transmission frequency: 868 MHz, range 100 - 300 m, CE compliant.

### ETIM 10 Characteristics

|   |                 |                             |               |
|---|-----------------|-----------------------------|---------------|
| <b>Suitable for dimmer</b>                          | ×               | <b>Power consumption</b>    | 3680 Watt     |
| <b>Suitable for pulse button</b>                    | ×               | <b>Number of relays</b>     | 1             |
| <b>Suitable for roller shutter switch</b>           | ×               | <b>RAL-number (similar)</b> | 9010          |
| <b>Suitable for venetian shutter switch</b>         | ×               | <b>Radio frequency</b>      | 868 Megahertz |
| <b>Suitable for venetian-/roller shutter switch</b> | ×               | <b>Code length (Bit)</b>    | 0             |
| <b>Suitable for switch</b>                          | ×               | <b>Number of commands</b>   | 0             |
| <b>In housing</b>                                   | ✓               |                             |               |
| <b>In tube base housing</b>                         | ×               |                             |               |
| <b>Printed circuit board/module</b>                 | ×               |                             |               |
| <b>Current supply</b>                               | 230 V AC        |                             |               |
| <b>Push button mode</b>                             | ×               |                             |               |
| <b>Switching mode</b>                               | ✓               |                             |               |
| <b>With manual radio transmitter</b>                | ×               |                             |               |
| <b>With radio coding device</b>                     | ×               |                             |               |
| <b>With radio controlled push button</b>            | ×               |                             |               |
| <b>Mounting method</b>                              | Surface mounted |                             |               |
| <b>Material</b>                                     | Plastic         |                             |               |
| <b>Material quality</b>                             | Thermoplastic   |                             |               |
| <b>Halogen free</b>                                 | ✓               |                             |               |
| <b>Surface protection</b>                           | Untreated       |                             |               |
| <b>Surface finishing</b>                            | Matt            |                             |               |
| <b>Type of fastening</b>                            | Other           |                             |               |
| <b>Colour</b>                                       | White           |                             |               |
| <b>Transparent</b>                                  | ×               |                             |               |
| <b>Suitable for degree of protection (IP)</b>       | IP20            |                             |               |

Created on: 16/12/2025

|   |       |
|---|-------|
| <b>Degree of protection (NEMA)</b>      | Other |
| <b>Modulation</b>                       | FM    |
| <b>Rolling code system</b>              | ×     |
| <b>Compatible with Apple HomeKit</b>    | ×     |
| <b>Compatible with Google Assistant</b> | ×     |
| <b>Compatible with Amazon Alexa</b>     | ×     |
| <b>IFTTT support available</b>          | ×     |